

Note: This datasheet may be out of date Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata Manufacturing Co., Ltd. ata.com/en/products/productdetail?partno=NFE31PT101C1E9%23

## NFE31PT101C1E9#

"#" indicates a package specification code.

In Production RoHS REACH

< List of part numbers with package codes > NFE31PT101C1E9L NFE31PT101C1E9K NFE31PT101C1E9B






Packaging

### Packaging Information

Specifications





: Electrode (in mm)

Quantity L 2000 180mm Embossed Tape Κ 330mm Embossed Tape 8000 В 500 Bulk(Bag)



Other Usage

For general

1 of 4

Minimum Order

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention



Note: This datasheet may be out of date. Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata Manufacturing Co., Ltd. ata.com/en/products/productdetail?partno=NFE31PT101C1E9%23

### NFE31PT101C1E9#

"#" indicates a package specification code.



The chip "EMIFIL" NFE31PT is a small size T-type circuit EMI suppression filter.

#### Features

- 1. Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4.22 to 2,200pF lineups can be used in signal lines.

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



2 of 4



Note: This datasheet may be out of date. Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata Manufacturing Co., Ltd. http://www.murata.com/en/products/productdetail?partno=NFE31PT101C1E9%23

NFE31PT101C1E9#

"#" indicates a package specification code.

## Specifications

Shape	SMD
Size Code (in mm)	3216
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.35mm
Width	1.6mm
Width Tolerance	±0.15mm
Thickness	1.6mm
Thickness Tolerance	±0.15mm
Rated Current	6A
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.034g
Number of Circuit	1
Insulation Resistance(min.)	1000ΜΩ
Rated Voltage	25Vdc
Withstanding Voltage	62.5Vdc
Capacitance	100pF
Capacitance Tolerance	80/-20%

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Note: This datasheet may be out of date Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata Manufacturing Co., Ltd. n/en/products/productdetail?partno=NFE31PT101C1E9%23

NFE31PT101C1E9#

"#" indicates a package specification code.

0

# Product Data




10 Insertion Loss (dB) NFE31PT220R1E9 20 NFE31PT470C1E9 NFE31PT101C1E9 30 NFE31PT221D1E9 NFE31PT471F1E9 NFE31PT152Z1E9 40 NFE31PT222Z1E 50 60 l 100 1000 2000 10 Frequency (MHz)

(50Ω - 50Ω)

Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications. Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

