

Note: This datasheet may be out of date. Please download the latest datasheet of NFE31ZT222Z1E9# from the official website of Murata Manufacturing Co., Ltd. ata.com/en/products/productdetail?partno=NFE31ZT222Z1E9%23

### NFE31ZT222Z1E9#

"#" indicates a package specification code.



< List of part numbers with package codes > NFE31ZT222Z1E9L NFE31ZT222Z1E9K NFE31ZT222Z1E9B





Packaging

L

Κ

В

#### Packaging Information


Specifications

Bulk(Bag)

180mm Embossed Tape

330mm Embossed Tape

10	





: Electrode (in mm)



Automotive Usage

Infotainment

1 of 4

Minimum Order

Quantity

2000

8000

500

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention



Note: This datasheet may be out of date. Please download the latest datasheet of NFE31ZT222Z1E9# from the official website of Murata Manufacturing Co., Ltd. ata.com/en/products/productdetail?partno=NFE31ZT222Z1E9%23

NFE31ZT222Z1E9#

"#" indicates a package specification code.



The chip "EMIFIL" NFE31ZT is a small size T-type circuit EMI suppression filter.

#### Features

- 1. Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4.22 to 2,200pF lineups can be used in signal lines.

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



2 of 4



Note: This datasheet may be out of date. Please download the latest datasheet of NFE31ZT222Z1E9# from the official website of Murata Manufacturing Co., Ltd. http://www.murata.com/en/products/productdetail?partno=NFE31ZT222Z1E9%23

NFE31ZT222Z1E9#

"#" indicates a package specification code.

## Specifications

Shape	SMD
Size Code (in mm)	3216
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.35mm
Width	1.6mm
Width Tolerance	±0.15mm
Thickness	1.6mm
Thickness Tolerance	±0.15mm
Rated Current	6A
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.034g
Number of Circuit	1
Insulation Resistance(min.)	1000ΜΩ
Rated Voltage	25Vdc
Withstanding Voltage	62.5Vdc
Capacitance	2200pF
Capacitance Tolerance	±50%

3 of 4

Attention This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Note: This datasheet may be out of date Please download the latest datasheet of NFE31ZT222Z1E9# from the official website of Murata Manufacturing Co., Ltd. n/en/products/productdetail?partno=NFE31ZT222Z1E9%23

# NFE31ZT222Z1E9#

"#" indicates a package specification code.

0

# Product Data




10 Insertion Loss (dB) NFE31ZT220R1E9 20 NFE31ZT470C1E9 NFE31ZT101C1E9 30 NFE31ZT221D1E9 NFE31ZT471F1E9 NFE31ZT152Z1E9 40 NFE31ZT222Z1E 50 60 l 100 1000 2000 10 Frequency (MHz)

(50Ω - 50Ω)

Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

