

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

OmniVS 230V 800VA 475W Line-Interactive UPS, USB port, C13 Outlets

MODEL NUMBER: OMNIVSINT800





Description

Tripp Lite's OMNIVSINT800 line interactive UPS system offers voltage regulation, surge suppression and long lasting battery support for personal computers, internetworking equipment and other sensitive electronics. Internal UPS circuits support entry level PC systems for up to 40 minutes during power failures so that connected equipment can be shut down without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 159 volts back to usable levels without using battery power. Offers complete desktop power protection in an attractive black tower configuration. Includes 4 outlets with battery support and AC surge suppression. USB port enables optional unattended system shutdown without data loss in the case of extended power failure, USB cable included. PowerAlert software available via free download. Built-in single line RJ phone suppression jacks protect modem, fax machine, cordless phone or other peripheral with a standard dialup/DSL phone connection. Built-in audible alarm and 4 front panel LEDs indicate line power status, battery power status, battery low/replace status and UPS overload. 800VA power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Supports battery replacement via built-in access panel.

Features

- OMNIVSINT800 Uninterruptible Power Supply offers voltage regulation, surge suppression and long lasting battery support
- · Supports entry level PCs up to 40 minutes during blackouts to enable shutdown without data loss
- Regulates brownouts as low as 159 volts back to usable levels without using battery power
- 4 IEC320 C13 outlets with complete AC surge suppression
- C14 inlet accepts user-supplied AC power cord with country specific plug
- USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- Single line phone suppression protects standard dialup/DSL phone connection
- Audible alarm and 4 front panel LEDs offer complete UPS and line power status information

Highlights

- 800VA tower 230V line interactive UPS
- Corrects brownouts as low as 159V without using battery power
- USB port, TEL/DSL protection
- C14 input and 4 C13 outlets

Package Includes

- OMNIVSINT800 line interactive UPS
- 2 C13 to C14 interconnection cables
- USB and phone line cables
- Owner's manual with warranty information



- 800VA power handling ability supports a variety of sensitive electronic equipment
- 4.3 minutes full load runtime (800VA), 10.8 minutes half load runtime (400VA)
- Supports battery replacement via built-in access panel
- Optional PDUBHV10 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- Attractive full color retail packaging

Specifications

| OVERVIEW | | | |
|--|---|--|--|
| UPC Code | 037332120960 | | |
| UPS Type | Line-Interactive | | |
| INPUT | | | |
| Rated input current (Maximum Load) | 2.4A | | |
| Nominal Input Voltage(s) Supported | 230V AC | | |
| UPS Input Connection Type | C14 inlet | | |
| UPS Input Connection Description | Attached 15cm line cord with C14 inlet. The C14 accepts a user-supplied AC power cord with country-specific plug. | | |
| UPS Input Cord Length (ft.) | 0.5 | | |
| UPS Input Cord Length (m) | 0.2 | | |
| Input Phase | Single-Phase | | |
| ОИТРИТ | | | |
| Output Volt Amp Capacity (VA) | 800 | | |
| Output Watt Capacity (Watts) | 475 | | |
| Nominal Voltage Details | 230V nominal output in battery mode | | |
| Frequency Compatibility | 50 / 60 Hz | | |
| Frequency Compatibility Details | Automatic frequency selection | | |
| Output Voltage Regulation (Battery Mode) | +/- 5% | | |
| Included Output Power Cables | Includes 2 C13 to C14 output power cables | | |
| Hot-Swap PDU options | PDUBHV10 (2U / 8 C13 outlets) | | |
| Output AC Waveform (AC Mode) | Sine wave | | |
| Output AC Waveform (Battery Mode) | PWM sine wave | | |
| Nominal Output Voltage(s) Supported | 220V; 230V; 240V | | |
| Output Receptacles | (4) C13 | | |
| Individually Controllable Load Banks | No | | |



| BATTERY | | |
|---|---|--|
| Battery Type | Valve Regulated Lead Acid (VRLA) | |
| Full Load Runtime (min.) | 4.3 min. (475w) | |
| Half Load Runtime (min.) | 10.8 min. (240w) | |
| Expandable Runtime | No | |
| DC System Voltage (VDC) | 12 | |
| Battery Recharge Rate (Included Batteries) | Less than 4.5 hours from 10% to 90% | |
| Battery Access | Battery access door | |
| Internal UPS Replacement Battery Cartridge | RBC51 | |
| Battery Replacement Description | Hot-swappable, user replaceable batteries | |
| VOLTAGE REGULATION | | |
| Voltage Regulation Description | Automatic voltage regulation (AVR) maintains line power operation with input voltage as low as 159 | |
| Undervoltage Correction | Input voltages between 159 and 199 are boosted by 14% | |
| USER INTERFACE, ALERTS & CONTROLS | | |
| Switches | 2 Switches control off/on power status and alarm-cancel/self-test operation | |
| Alarm Cancel Operation | Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status | |
| Audible Alarm | Audible alarm indicates power-failure and low-battery conditions | |
| LED Indicators | 4 LEDs indicate line power, battery power, overload and battery low/replace status | |
| SURGE / NOISE SUPPRESSION | | |
| UPS AC Suppression Joule Rating | 340 | |
| UPS AC Suppression Response Time | Instantaneous | |
| UPS Dataline Suppression | 1 line TEL/DSL (1 in / 1 out) | |
| EMI / RFI AC Noise Suppression | Yes | |
| PHYSICAL | | |
| Primary Form Factor | Tower | |
| Installation Form Factors Supported with Included Accessories | Tower | |
| Installation Form Factors Supported with Optional Accessories | Wallmount (UPSWM - tower mounting kit) | |
| Primary UPS Depth (mm) | 191 | |
| Primary UPS Height (mm) | 274 | |





| Primary UPS Width (mm) | 132 | |
|--|---|--|
| Shipping Dimensions (hwd / cm) | 24.64 x 19.05 x 34.80 | |
| Shipping Dimensions (hwd / in.) | 9.70 x 7.50 x 13.70 | |
| Shipping Weight (kg) | 9.94 | |
| Shipping Weight (lbs.) | 21.92 | |
| UPS Housing Material | PVC | |
| UPS Power Module Dimensions (hwd, cm) | 27.43 x 13.21 x 19.05 | |
| UPS Power Module Dimensions (hwd, in.) | 10.8 x 5.2 x 7.5 | |
| UPS Power Module Weight (kg) | 8.85 | |
| UPS Power Module Weight (lbs.) | 19.5 | |
| ENVIDONMENTAL | | |
| Charatina Tannanatura Dansa | 20 to 1404 de mano Folyandroit / 0 to 140 de mano Coloine | |
| Operating Temperature Range | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius | |
| Storage Temperature Range | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius | |
| Relative Humidity | 0 to 95%, non-condensing | |
| Battery Mode BTU / Hr. (Full Load) | 458 | |
| A C B A I F C C C C C C C C C C C C C C C C C C | | |
| AC Mode Efficiency Rating (100% Load) | 97% | |
| | 97% | |
| Load) | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert | |
| COMMUNICATIONS | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at | |
| COMMUNICATIONS PowerAlert Software | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert | |
| COMMUNICATIONS PowerAlert Software Communications Cable | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description Communications Interface | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description Communications Interface LINE / BATTERY TRANSFER | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported USB | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description Communications Interface LINE / BATTERY TRANSFER Transfer Time Low Voltage Transfer to Battery | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported USB 2-4 milliseconds | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description Communications Interface LINE / BATTERY TRANSFER Transfer Time Low Voltage Transfer to Battery Power (Setpoint) | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported USB 2-4 milliseconds | |
| COMMUNICATIONS PowerAlert Software Communications Cable WatchDog Compatibility Network Management Card Description Communications Interface LINE / BATTERY TRANSFER Transfer Time Low Voltage Transfer to Battery Power (Setpoint) | For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert USB interface cable included Supports Watchdog application, OS and hard-reboot restart options for remote applications Network management not supported USB 2-4 milliseconds 159 | |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| STANDARDS & COMPLIANCE | | |
|---|--|--|
| UPS Certifications | Tested to UL1778 (USA); CE; Tested to GOST (Russia); Tested to SASO (Saudi Arabia); Tested to IRAM (Argentina) | |
| WARRANTY | | |
| Product Warranty Period (International) | 2-year limited warranty | |
| Product Warranty Period (Mexico) | 2-year limited warranty | |
| Product Warranty Period (Puerto Rico) | 2-year limited warranty | |

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies