

PRODUCT-DETAILS

OT25F3C OT25F3C CHANGE-OVER SWITCH



| General Information | | |
|---|--|---------------|
| Extended Product Type | OT25F3C | |
| Product ID | 1SCA104863R1001 | |
| EAN | 6417019390062 | |
| Catalog Description | OT25F3C CHANGE-OVER SWITCH | |
| Long Description | 25A Manual Change-Over Switch, Handle and shaft need to be ordered separately, Open transition | |
| Circular Value | | |
| Conflict Minerals Reporting Template (CMRT) | 9AKK108467A5658 | |
| REACH Declaration | 1SCC011021D0201 | |
| RoHS Information | 1SCC011020D0201 | |
| Ordering | | |
| Minimum Order Quantity | 1 piece | |
| Customs Tariff Number | 85365080 | |
| Country of Origin | Finland (FI) | |
| © 2023 ABB. All rights reserved. | 2023/11/20 Subject to change | ge without no |

| Popular Downloads | | |
|---|------------|--|
| Data Sheet, Technical Information | | 1SCC303003C0201 |
| Instructions and Manuals | | 1SCC301054M0006 |
| Dimensions | | |
| Product Net Width | | 55 mm 2.17 in |
| Product Net Height | | 68 mm 2.68 in |
| Product Net Depth / Length | | 68 mm 2.68 in |
| Product Net Weight | | 0.55 kg 1.21 lb |
| Technical | | |
| Rated Operational Current AC-21A (I _e) | | (380 415 V) 25 A (500 V) 25 A (690 V) 25 A |
| Rated Operational Current AC-22A (I _e) | | (380 415 V) 25 A (500 V) 25 A (690 V) 25 A |
| Rated Operational Current AC-23A (I _e) | | (380 415 V) 20 A (500 V) 20 A (690 V) 11 A |
| Rated Operational Power AC-23A (P _e) | | (380 415 V) 9 kW (500 V) 9 kW (690 V) 9 kW |
| Conventional Free-air Thermal Current (I _{th}) | | Θ = 40 °C 32 A |
| Conventional Thermal Current (I _{the}) | | Fully Enclosed 32 A |
| Rated Impulse Withstand /oltage (U _{imp}) | | 8 kV |
| Rated Insulation Voltage (U _i) | | 750 V |
| Rated Operational Voltage | | 750 V |
| Rated Short-time Nithstand Current Low Voltage (I _{cw}) | | for 1 s 0.5 kiloampere rms |
| Power Loss | | 0.6 W |
| Pollution Degree | | 3 |
| Handle Color | | Black |
| Handle Type | | Handle and shaft not included |
| Switches Operating Mechanism | | Mechanism on Top of the Switch |
| Distance Between Phases | | Standard |
| Position of Line Terminals | | Top In - Bottom Out, Bottom In - Top Out |
| © 2023 ABB. All rights reserved. | 2023/11/20 | Subject to change without r |

| Operating Mode | Front operated |
|----------------------|--------------------|
| Standards | UL 98 / IEC60947-3 |
| Mounting Type | Base mounting |
| Number of Poles | 3 |
| Cable Cross-Section | 0.75 10 mm² |
| Degree of Protection | Front IP20 |
| Transition Type | Open |

Technical UL/CSA

| Ampere Rating | 25 A |
|-------------------|---------------------------|
| Horsepower Rating | (acc. to UL 200 V) 7.5 Hp |
| UL/CSA | (acc. to UL 208 V) 7.5 Hp |
| | (acc. to UL 240 V) 7.5 Hp |
| | (acc. to UL 480 V) 15 Hp |
| | (acc. to UL 600 V) 20 Hp |

Environmental

RoHS Status Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Certificates and Declarations

| Declaration of Conformity - CE | 1SCC303019D2702 |
|--------------------------------|-----------------|
| REACH Declaration | 1SCC011021D0201 |

Container Information

| Package Level 1 Units | 1 piece |
|-------------------------|---------------|
| Package Level 1 Width | 80 mm |
| | 3.15 in |
| Package Level 1 Depth / | 108 mm |
| Length | 4.25 in |
| Package Level 1 Height | 79 mm |
| | 3.11 in |
| Package Level 1 Gross | 0.25 kg |
| Weight | 0.55 lb |
| Package Level 1 EAN | 6417019390062 |

Classifications

| Object Classification Code | Q |
|----------------------------|--|
| ETIM 7 | EC000216 - Switch disconnector |
| ETIM 8 | EC000216 - Switch disconnector |
| ETIM 9 | EC000216 - Switch disconnector (low voltage) |
| UNSPSC | 39122233 |

IDEA Granular Category Code (IGCC) 5290 >> Disconnect switch

OT25F3C 4

| eClass | V11.1 : 27371403 |
|--------------------|--|
| WEEE Category | 5. Small Equipment (No External Dimension More Than 50 cm) |
| E-Number (Finland) | 3601430 |
| E-Number (Sweden) | 3171261 |

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Switches \rightarrow Change-over\ and\ Transfer\ Switches \rightarrow Manual\ Change-over\ Switches$

