

# TDM / TDMH / TDML SERIES


### Delay-on-Make Timer







### Wiring Diagram



Relay contacts are isolated.

### **Ordering Information**

MODEL	INPUT VOLTAGE	DELAY RANGE
TDM120AL	120VAC	1 - 1023s in 1s increments
TDM12DL	12VDC	1 - 1023s in 1s increments
TDM230AL	230VAC	1 - 1023s in 1s increments
TDM24AL	24VAC	1 - 1023s in 1s increments
TDM24DL	24VDC/28VDC	1 - 1023s in 1s increments
TDMH120AL	120VAC	10 - 10230s in 10s increments
TDMH24AL	24VAC	10 - 10230s in 10s increments
TDML110DL	110VDC	0.1 - 102.3s in 0.1s increments
TDML120AL	120VAC	0.1 - 102.3s in 0.1s increments
TDML12DL	12VDC	0.1 - 102.3s in 0.1s increments
TDML24DL	24VDC/28VDC	0.1 - 102.3s in 0.1s increments

If you don't find the part you need, call us for a custom product 800-843-8848

### **Description**

The TDM/TDMH/TDML Series is a delay-on-make timer that combines accurate digital circuitry with isolated, DPDT relay contacts in an industry standard 8-pin plug-in package. DIP switch adjustment allows precise selection of the time delay over the full time delay range. The TDM/TDMH/TDML Series is the product of choice for custom control panel and OEM designers.

#### Operation (Delay-on-Make)

Upon application of input voltage, the time delay begins. The output is de-energized before and during the time delay. At the end of the time delay, the output relay energizes and remains energized until input voltage is removed.

Reset: Removing input voltage resets the time delay and output.

### **Features & Benefits**

FEATURES	BENEFITS
Wide delay range (0.1s to 2.8h)	User selectable via DIP switches for fine tuning to individual applications.
Microcontroller based	Repeat Accuracy + / - 0.1%
Dip switch adjustment	Provides first time setting accuracy of +/-2%
Setting accuracy +/-2%	Provides flexibility for use in most applications
LED indication	Provides visual indication of time delay status
Isolated 10A, DPDT output contacts	Allows control of loads for AC or DC voltages

#### Accessories



#### **BZ1 Front Panel Mount Kit**

Provides an easy method of through-the-panel mounting of 8- or 11-pin plug-in timers, flashers, and other controls.



#### NDS-8 Octal 8-pin Socket

8-pin 35mm DIN rail or surface mount. Surface mounted with two #6 screws or snaps onto a 35 mm DIN rail. Uses PSC8 hold-down clips.



#### **PSC8 or PSC11 Hold-down Clips**

Securely mounts plug-in controls in any position. Provides protection against vibration. Use PSC8 with NDS-8 Octal Socket or PSC11 with NDS-11 Socket. Sold in sets of two.



#### P1011-6 Octal Socket for UL listing\*

8-pin surface mount socket with binder head screw terminals. Rated 10A @ 600VAC.



### C103PM (AL) DIN Rail

35 mm aluminum DIN rail available in a 36 in. (91.4 cm) length.



# TDM / TDMH / TDML SERIES

### **Specifications**

**Time Delay** 

Type Digital integrated circuitry
Range\* 0.1 - 102.3s in 0.1s increments
1 - 1023s in 1s increments
10 - 10,230s in 10s increments

Repeat Accuracy ±0.1% or 20ms, whichever is greater

Setting Accuracy ±2% or 50ms, whichever is greater

Reset Time ≤ 50ms

**Recycle Time** During Timing - TDMH:  $\leq$  500ms TDM, TDML:  $\leq$  300ms

Time Delay vs. Temperature

& Voltage ±29

**Indicator** LED glows during timing; relay is

de-energized

Input

**Voltage** 12, 24, or 110 VDC; 24, 120, or 230VAC **Tolerance** 

**12VDC & 24VDC/AC** -15% - 20% 110VAC/DC to 230VAC -20% - 10% AC Line Frequency 50/60 Hz Power Consumption ≤ 2.25W

Output

**Type** Electromechanical relay

**Form** DPDT

Rating 10A resistive @ 120/240VAC & 28VDC;

1/3 hp @ 120/240VAC

**Life** Mechanical - 1 x10<sup>7</sup>; Electrical - 1 x 10<sup>6</sup>

**Protection** 

**Polarity** DC units are reverse polarity protected

**Isolation Voltage** ≥ 1500V RMS input to output

Mechanical

**Mounting** Plug-in socket

**Dimensions H** 81.3 mm (3.2"); **W** 60.7 mm (2.39");

**D** 45.2 mm (1.78")

**Termination** Octal 8-pin plug-in


**Environmental** 

Operating/Storage


**Temperature** -20° to 65°C / -30° to 85°C

Weight  $\approx 6 \text{ oz } (170 \text{ g})$ 

### **Binary Switch Operation**



### **Function Diagram**



Time

<sup>\*</sup>For CE approved applications, power must be removed from the unit when a switch position is changed.

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Littelfuse:

TDM24DL TDML110DL TDM12DL TDML120AL TDM230AL TDML24DL TDMH24AL TDM24AL TDMH120AL TDM120AL TDML12DL