Note: This datasheet may be out of date.

Please download the latest datasheet of BLM15AX100SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM15AX100SZ1%23

"#" indicates a package specification code.

# BLM15AX100SZ1#









< List of part numbers with package codes >

BLM15AX100SZ1J

BLM15AX100SZ1B

BLM15AX100SZ1D



### Appearance & Shape







1.0±0.05



(in mm)



## **Packaging Information**

			Standard
	Packaging	Specifications	Packing
			Quantity
	J	330mm Paper Tape	50000
	В	Bulk(Bag)	1000
	D	180mm Paper Tape	10000



### **Applications**

Automotive Usage

Infotainment

1 of 4

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



## BLM15AX100SZ1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM15AX100SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM15AX100SZ1%23

"#" indicates a package specification code.



The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz). Because of newly developed ferrite material, BLM15AX has been realized lower DC resistance and larger rated current than BLM15AG series. In addition, its performance change by stresses like heat shock is less than other ferrite beads. So, the noise suppression performance becomes stable.

2 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



BLM15AX100SZ1#

Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM15AX100SZ1%23

Please download the latest datasheet of BLM15AX100SZ1# from the official website of Murata

Note: This datasheet may be out of date.

"#" indicates a package specification code.



# **Specifications**

Shape	SMD
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.001g
Number of Circuit	1
Rated Current (at 85°C)	1.74A
Rated Current (at 125°C)	1.74A
DC Resistance(max.)	0.015Ω
Impedance (at 100MHz)	10Ω
Impedance (at 100MHz) Tolerance	±5Ω
Size Code (in mm)	1005

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Note: This datasheet may be out of date. Please download the latest datasheet of BLM15AX100SZ1# from the official website of Murata


http://www.murata.com/en-us/products/productdetail?partno=BLM15AX100SZ1%23


Manufacturing Co., Ltd.

"#" indicates a package specification code.

# BLM15AX100SZ1#







Impedance-Frequency Characteristics

**Equivalent Circuit** 

4 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

