

NOT RECOMMENDED FOR NEW DESIGN USE PAM8304



Pin Assignments

2

3

4

PAM8303D

ULTRA LOW EMI, 3W FILTERLESS MONO CLASS-D AUDIO POWER AMPLIFIER

(8

67

6

(5

8

7

6

5

U-DFN3030-8

P8303D XXXXYW

MSOP-8

Top View

P8303D XXXXYV

Top View


Description

The PAM8303D is a 3W mono filterless Class-D amplifier with high PSRR and differential input that eliminate noise and RF rectification.

Features like 90% efficiency and small PCB area make the PAM8303D Class-D amplifier ideal for cellular handsets. The filterless architecture requires no external output filter, fewer externa components, less PCB area and lower system costs, and simplifies application design.

The PAM8303D features short circuit protection and thermal shutdown.

The PAM8303D is available in MSOP-8 and U-DFN3030-8 packages.



Features

- Ultra Low EMI, -20dB Better Than FCC Class-B @ 300MHz
- High Efficiency up to 90% @1W with an 8 Ω Speaker
- Shutdown Current <1µA
- 3W@10% THD Output with a 4Ω Load at 5V Supply
- Demanding Few External Components Superior Low Noise without Input Supply Voltage from 2.8V to 5.5V
- Short Circuit Protection
- Thermal Shutdown
- Available in Space Saving Packages: MSOP-8, U-DFN3030-8
- Totally Lead-Free & Fully RoHS Compliant (Note 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)

Applications

2

3


4

- Cellular Phones/Smart Phones
- MP4/MP3
- GPS
- Digital Photo Frame Electronic
- Dictionary Portable Game
- Machines


- Notes: 1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS), 2011/65/EU (RoHS 2) & 2015/863/EU (RoHS 3).compliant.
 - 2. See https://www.diodes.com/quality/lead-free/ for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
 - Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.



Typical Applications Circuit



Functional Block Diagram





Absolute Maximum Ratings (@T_A = +25°C, unless otherwise specified.)

These are stress ratings only and functional operation is not implied. Exposure to absolute maximum ratings for prolonged time periods may affect device reliability. All voltages are with respect to ground.

| Parameter | Rating | Unit |
|------------------------------|------------------------------|------|
| Supply Voltage | 6.0 | V |
| Input Voltage | -0.3 to V _{DD} +0.3 | V |
| Maximum Junction Temperature | 150 | |
| Storage Temperature | -65 to +150 | °C |
| Soldering Temperature | 250, 10 sec | |

Recommended Operating Conditions (@TA = +25°C, unless otherwise specified.)

| Parameter | Rating | Unit |
|----------------------------|-------------|------|
| Supply Voltage Range | 2.8 to 5.5 | V |
| Ambient Temperature Range | -40 to +85 | °C |
| Junction Temperature Range | -40 to +125 | °C |
| | | |

Thermal Information


| | | | | · |
|--|-------------|-----------------|------|------|
| Parameter | Package | Symbol | Max | Unit |
| Thermal Resistance (Junction to Ambient) | MSOP-8 | 0 | 180 | |
| | U-DFN3030-8 | θ _{JA} | 47.9 | °C/W |
| Thermal Resistance (Junction to Case) | MSOP-8 | οιθ | 75 | |




$\label{eq:Electrical Characteristics} (@T_A = +25^{\circ}C, V_{DD} = 5V, Gain = 2V/V, R_L = L(33\mu H) + R + L(33\mu H), unless otherwise specified.)$


| Symbol | Parameter | Test Conditions | | Min | Тур | Max | Unit | |
|------------------------------------|--|--|------------------------|------|------|------|------|--|
| Vdd | Supply Voltage | - | - | 2.8 | - | 5.5 | V | |
| | | V _{DD} = 5.0V | 2.85 | 3.00 | - | | | |
| | THD+N = 10%, f = 1KHz, R = 4Ω | V _{DD} = 3.6V | 1.65 | 1.80 | - | w | | |
| | | V _{DD} = 3.2V | 1.20 | 1.35 | - | | | |
| | | V _{DD} = 5.0V | 2.50 | 2.66 | - | | | |
| | THD+N = 1%, f = 1KHz, R = 4 Ω | V _{DD} = 3.6V | 1.15 | 1.30 | - | w | | |
| _ | | | V _{DD} = 3.2V | 0.85 | 1.0 | - | 1 | |
| Po | Output Power | THD+N = 10%, f = 1KHz, R = 8Ω | VDD = 5.0V | 1.65 | 1.80 | - | | |
| | | | V _{DD} = 3.6V | 0.75 | 0.90 | - | w | |
| | | | V _{DD} = 3.2V | 0.55 | 0.70 | - | | |
| | | | VDD = 5.0V | 1.3 | 1.5 | - | | |
| | THD+N = 1%, f = 1KHz, R = 8Ω | V _{DD} = 3.6V | 0.55 | 0.72 | - | w | | |
| | | $V_{DD} = 3.2V$ | 0.40 | 0.55 | - | | | |
| | | $V_{DD} = 5.0V, P_{O} = 1W, R = 8\Omega$ | | - | 0.28 | 0.35 | | |
| | | $V_{DD} = 3.6V, P_O = 0.1W, R = 8\Omega$ | f = 1kHz | - | 0.40 | 0.45 | % | |
| | Total Harmonic Distortion Plus | $V_{DD} = 3.2V, P_0 = 0.1W, R = 8\Omega$ | | - | 0.55 | 0.60 | 1 | |
| THD+N | Noise | $V_{DD} = 5.0V, P_0 = 0.5W, R = 4\Omega$ | | - | 0.20 | 0.25 | | |
| | | $V_{DD} = 3.6V, P_{O} = 0.2W, R = 4\Omega$ | f = 1kHz | - | 0.35 | 0.40 | ~ % | |
| | $V_{DD} = 3.2V, P_0 = 0.1W, R = 4\Omega$ | | - | 0.5 | 0.55 | | | |
| | | $V_{DD} = 3.2V, P_{O} = 0.1W, R = 402$ | f = 217Hz | - | -63 | -55 | | |
| PSRR Power Supply Ripple Rejection | V_{DD} = 3.6V, Inputs AC-Grounded with C _{IN} = 1µF | f = 1kHz | - | -62 | -55 | - | | |
| | | f = 10kHz | - | -52 | -40 | dB | | |
| Dyn | Dynamic Range | $V_{DD} = 5V$, THD = 1%, R = 8 Ω | f = 1kHz | 85 | 95 | - | İ | |
| | Output Nieles | | No A-Weighting | - | 50 | 100 | | |
| V _N | Output Noise | Inputs AC-Grounded | A-Weighting | - | 30 | 60 | μV | |
| CMRR | Common Mode Rejection Ratio | VIC = 100m, VPP, f =1kHz | | 40 | 63 | - | dB | |
| | Deals Efficiency | RL = 8Ω, THD = 10% | 6 41-11- | 85 | 90 | - | % | |
| η Peak Efficiency | $R_L = 4\Omega$, THD = 10% | f = 1kHz | 80 | 86 | - | % | | |
| | | VDD = 5.0V | | - | 7.5 | - | mA | |
| Iq Quiescent Current | V _{DD} = 3.6V | R = 8Ω | - | 4.6 | - | mA | | |
| | | $V_{DD} = 3.0V$ | 1 | - | 3.6 | - | mA | |
| I _{SD} | Shutdown Current | V _{DD} = 3.0V to 5.0V | V _{SD} = 0.3V | - | 0.5 | 2.0 | μA | |
| | | CSP Package, High Side PMOS | V _{DD} = 5.0V | - | 280 | 350 | mΩ | |
| Static Drain-to-Source | plus Low Side NMOS, | V _{DD} = 3.6V | - | 300 | 375 | mΩ | | |
| | I = 500mA | V _{DD} = 3.0V | - | 325 | 400 | mΩ | | |
| Rds(on) | On-State Resistor | MSOP/DFN package, | V _{DD} = 5.0V | - | 365 | 420 | mΩ | |
| | High Side PMOS plus | V _{DD} = 3.6V | - | 385 | 450 | mΩ | | |
| | Low Side NMOS, I = 500mA | VDD = 3.0V | - | 410 | 500 | mΩ | | |
| R _{IN} | Input Resistance | - | 1 | - | 150 | - | kΩ | |
| f _{SW} | Switching Frequency | V _{DD} = 3V to 5V | | - | 380 | - | kHz | |
| Gv | Closed Loop Gain | $V_{DD} = 3V \text{ to } 5V$ | | - | 300 | - | dB | |
| | Output Offset Voltage | Input AC-Ground, $V_{DD} = 5V$ | | - | 10 | 50 | mV | |
| Voe | | | | | | | | |
| V _{OS} V _{IH} | Enable Input High Voltage | $V_{DD} = 5V$ | | 1.5 | - | - | V | |

































5





Test Setup for Performance Testing



Notes
The AP AUX-0025 low pass filter is necessary for Class-D amplifier measurement with AP analyzer.
Two 22μH inductors are used in series with load resistor to emulate the small speaker for efficiency measurement

Input Resistance (R_I)

The input resistors (RI) set the gain of the amplifier according to Equation 1.

Gain =
$$\frac{2x150k\Omega}{R_I} \left(\frac{V}{V} \right)$$

Resistor matching is very important in fully differential amplifiers. The balance of the output on the reference voltage depends on matched ratios of the resistors. CMRR, PSRR, and cancellation of the second harmonic distortion diminish if resistor mismatch occurs. Therefore, it is recommended to use 1% tolerance resistors or better to keep the performance optimized. Matching is more important than overall tolerance. Resistor arrays with 1% matching can be used with a tolerance greater than 1%.

Place the input resistors very close to the PAM8303D to limit noise injection on the high impedance nodes.

For optimal performance the gain should be set to $2X (R_I = 150k)$ or lower. Lower gain allows the PAM8303D to operate at its best, and keeps a high voltage at the input making the inputs less susceptible to noise. In addition to these features, higher value of R_I minimizes pop noise.

Input Capacitors (Ci)

In the typical application, an input capacitor, C_i, is required to allow the amplifier to bias the input signal to the proper DC level for optimum operation. In this case, Ci and the minimum input impedance R_I form is a high-pass filter with the corner frequency determined in the follow equation:



It is important to consider the value of C_i as it directly affects the low frequency performance of the circuit. For example, when R_i is 150k Ω and the specification calls for a flat bass response are down to 150Hz. Equation is reconfigured as followed:



When input resistance variation is considered, the C_I is 7nF, so one would likely choose a value of 10nF. A further consideration for this capacitor is the leakage path from the input source through the input network (C_I , $R_I + R_F$) to the load. This leakage current creates a DC offset voltage at the input to the amplifier that reduces useful headroom, especially in high gain applications.

For this reason, a low-leakage tantalum or ceramic capacitor is the best choice. When polarized capacitors are used, the positive side of the capacitor should face the amplifier input in most applications as the DC level is held at $V_{DD}/2$, which is likely higher than the source DC level. Please note that it is important to confirm the capacitor polarity in the application.



Application Information (Cont.)

Decoupling Capacitor (Cs)

The PAM8303D is a high-performance CMOS audio amplifier that requires adequate power supply decoupling to ensure the output tota harmonic distortion (THD) as low as possible. Power supply decoupling also prevents the oscillations causing by long lead length between the amplifier and the speaker.

The optimum decoupling is achieved by using two different types of capacitors that target on different types of noise on the power supply leads. For higher frequency transients, spikes, or digital hash on the line, a good low equivalentseries- resistance (ESR) ceramic capacitor, typically 1µF, is placed as close as possible to the device each V_{DD} and PV_{DD} pin for the best operation. For filtering lower frequency noise signals, a large ceramic capacitor of 10µF or greater placed near the audio power amplifier is recommended.

How to Reduce EMI

Most applications require a ferrite bead filter for EMI elimination shown at Figure 1. The ferrite filter reduces EMI around 1MHz and higher. When selecting a ferrite bead, choose one with high impedance at high frequencies, but low impedance at low frequencies.




Figure 1: Ferrite Bead Filter to Reduce EMI

In order to reduce power consumption while not in use, the PAM8303D contains shutdown circuitry that is used to turn off the amplifier's bias circuitry. This shutdown feature turns the amplifier off when logic low is placed on the SD pin. By switching the shutdown pin connected to GND, the PAM8303D supply current draw will be minimized in idle mode.

Shutdown Operation

In order to reduce power consumption while not in use, the PAM8303D contains shutdown circuitry that is used to turn off the amplifier's bias circuitry. This shutdown feature turns the amplifier off when logic low is placed on the pin. By switching the shutdown pin connected to GND, the PAM8303D supply current draw will be minimized in idle mode.

Under Voltage Lock-Out (UVLO)

The PAM8303D incorporates circuitry designed to detect low supply voltage. When the supply voltage drops to 2.3V or below, the PAM8303D goes into a state of shutdown, and the device comes out of its shutdown state and restore to normal function only when reset the power supply or SD pin.

Thermal protection on the PAM8303D prevents the device from damage when the internal die temperature exceeds +135°C. There is a 15°C tolerance on this trip point from device to device. Once the die temperature exceeds the set point, the device will enter the shutdown state and the outputs are disabled. This is not a latched fault. The thermal fault is cleared once the temperature of the die decreased by 30°C. This large hysteresis will prevent motor boating sound well and the device begins normal operation at this point with no external system interaction.

POP and Click Circuitry

The PAM8303D contains circuitry to minimize turn-on and turn-off transients or "click and pops", where turn-on refers to either power supply turnon or device recover from shutdown mode. When the device is turned on, the amplifiers are internally muted. An internal current source ramps up the internal reference voltage. The device will remain in mute mode until the reference voltage reach half supply voltage, 1/2 V_{DD}. As soon as the reference voltage is stable, the device will begin full operation. For the best power-off pop performance, the amplifier should be set in shutdown mode prior to removing the power supply voltage.



Application Information (Cont.)


PCB Layout Guidelines

Grounding

It is recommended to use plain grounding or separate grounds. Do not use one line connecting power GND and analog GND. Noise currents in the output power stage need to be returned to output noise ground and nowhere else. When these currents circulate elsewhere, they may gel into the power supply, or the signal ground, etc, even worse, they may form a loop and radiate noise. Any of these instances results in degraded amplifier performance. The output noise ground that the logical returns for the output noise currents associated with Class-D switching must tie to system ground at the power exclusively. Signal currents for the inputs, reference need to be returned to quite ground. This ground only ties to the signal components and the GND pin. GND then ties to system ground.

Power Supply Line

As same to the ground, V_{DD} and PV_{DD} need to be separately connected to the system power supply. It is recommended that all the trace could be routed as short and thick as possible. For the power line layout, just imagine water stream, any barricade placed in the trace (shown in Figure 2) could result in the bad performance of the amplifier.



Components Placement


Decoupling capacitors-As previously described, the high-frequency 1µF decoupling capacitors should be placed as close to the power supply terminals (V_{DD} and PV_{DD}) as possible. Large bulk power supply decoupling capacitors (10µF or greater) should be placed near the PAM8303D on the PV_{DD} terminal.

Input resistors and capacitors need to be placed very close to input pins.

Output filter - The ferrite EMI filter should be placed as close to the output terminals as possible for the best EMI performance, and the capacitors used in the filters should be grounded to system ground.




Ordering Information





Package Outline Dimensions


Please see http://www.diodes.com/package-outlines.html for the latest version.





Suggested Pad Layout

Please see http://www.diodes.com/package-outlines.html for the latest version.





IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2020, Diodes Incorporated

www.diodes.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Diodes Incorporated: PAM8303DBSC