

## Adafruit INA219 FeatherWing

PRODUCT ID: 3650

IN STOCK

1

ADD TO CART

1-9


10-99

100+

ADD TO WISHLIST

[DESCRIPTION](#)

[TECHNICAL DETAILS](#)



## DESCRIPTION

The **INA219 FeatherWing** makes power-monitoring problems a thing of the past. Instead of struggling with two multimeters, you can just use the handy INA219B chip on this breakout to

both measure both the high side voltage and DC current draw over I2C with 1% precision. **Works with any and all Feathers!** Communicates over I2C so its super-simple to use, you can even change the I2C address to have up to 4 of these Wings on one Feather.

Many current-measuring devices are only good for *low side* measuring. That means that unless you want to get a battery involved, you have to stick the measurement resistor between the target ground and true ground. This can cause problems with circuits since electronics tend to not like it when the ground references change and move with varying current draw. This chip is much smarter - it can handle high side current measuring, up to +26VDC, even though it is powered with 3.3V. It will also report back that high side voltage, which is great for tracking battery life or solar panels.

A precision amplifier measures the voltage across the 0.1 ohm, 1% sense resistor. Since the amplifier maximum input difference is  $\pm 320\text{mV}$  this means it can measure up to  $\pm 3.2$  Amps. With the internal 12 bit ADC, the resolution at  $\pm 3.2\text{A}$  range is 0.8mA. With the internal gain set at the minimum of div-8, the max current is  $\pm 400\text{mA}$  and the resolution is 0.1mA. Advanced hackers can remove the 0.1 ohm current sense resistor and replace it with their own to change the range (say a 0.01 ohm to measure up 32 Amps with a resolution of 8mA)

[We have a detailed tutorial for the INA219 that will do all the gain, range and math for you - just plug and go with Arduino or CircuitPython!](#)

---

## TECHNICAL DETAILS

Product Dimensions: 51.0mm x 22.8mm x 3.6mm / 2.0" x 0.9" x 0.1"

Product Weight: 3.4g / 0.1oz



---

## MAY WE ALSO SUGGEST...



INA219 High Side DC




Adafruit Power Relay




Adafruit Feather M0 Basic




Adalogger FeatherWing -




Adafruit Feather Huzzah



DC Motor + Stepper



FeatherWing Proto -



Adafruit Feather 32u4



Adafruit Huzzah32 -



Adafruit Feather 32u4

[CONTACT](#)

[SUPPORT](#)

[DISTRIBUTORS](#)

[EDUCATORS](#)

[JOBS](#)

[FAQ](#)

[SHIPPING & RETURNS](#)

[TERMS OF SERVICE](#)

[PRIVACY & LEGAL](#)

[ABOUT US](#)

*"The art of progress is to preserve order amid change and to preserve change amid order"* - [Alfred North Whitehead](#)

ENGINEERED IN NYC [Adafruit](#)®



4.9 ★★★★★  
Google  
Customer Reviews