

Is Now Part of



# **ON Semiconductor**®

# To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="mailto:www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to <a href="mailto:Fairchild\_questions@onsemi.com">Fairchild\_questions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or unavteries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor and is officers, employees, uniotificated use, even if such claim any manner.



**KSA940** 

### **Vertical Deflection Output Power Amplifier**

Complement to KSC2073



1.Base 2.Collector 3.Emitter

## **PNP Epitaxial Silicon Transistor**


Absolute Maximum Ratings  $T_C=25^{\circ}C$  unless otherwise noted

Symbol	Parameter	Ratings	Units	
V <sub>CBO</sub>	Collector-Base Voltage	- 150	V	
V <sub>CEO</sub>	Collector-Emitter Voltage	- 150	V	
V <sub>EBO</sub>	Emitter-Base Voltage	- 5	V	
I <sub>C</sub>	Collector Current	- 1.5	А	
I <sub>B</sub>	Base Current	- 0.5	А	
P <sub>C</sub>	Collector Dissipation (T <sub>a</sub> =25°C)	1.5	W	
P <sub>C</sub>	Collector Dissipation (T <sub>C</sub> =25°C)	25	W	
TJ	Junction Temperature	150	°C	
T <sub>STG</sub>	Storage Temperature	- 55 ~ 150	°C	

### Electrical Characteristics ${\rm T_{C}=25^{\circ}C}$ unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
I <sub>CBO</sub>	Collector Cut-off Current	$V_{CB} = -120V, I_E = 0$			- 10	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	V <sub>EB</sub> = - 5V, I <sub>C</sub> = 0			- 10	μA
h <sub>FE</sub>	DC Current Gain	V <sub>CE</sub> = - 10V, I <sub>C</sub> = - 500mA	40	75	140	
V <sub>CE</sub> (sat)	Collector-Emitter Saturation Voltage	I <sub>C</sub> = - 500mA, I <sub>B</sub> = - 50mA			- 1.5	V
V <sub>BE</sub> (on)	Base-Emitter ON Voltage	V <sub>CE</sub> = - 10V, I <sub>C</sub> = - 500mA	- 0.65	- 0.75	- 0.85	V
f <sub>T</sub>	Current Gain Bandwidth Product	V <sub>CE</sub> = - 10V, I <sub>C</sub> = - 500mA		4		MHz
C <sub>ob</sub>	Output Capacitance	$V_{CB} = -10V, I_E = 0$ f = 1MHz		55		pF

KSA940



©2000 Fairchild Semiconductor International

Rev. A, February 2000



ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

 ON Semiconductor:

 KSA940
 KSA940TSTU
 KSA940H2TU
 KSA940TU