
## **SMT Jumper Link**

---



- ➤ Designed to link PCB tracks where through hole links are not possible.
- ➤ Typical applications include use on aluminium backplanes in power applications.
- ▶ High current.
- **Small footprint.**
- Low profile options available for space saving design.



## **SPECIFICATION 12.3mm LONG** → Materials Material: Copper Alloy (\$1621, \$1911) Copper (S1731) Finish: See Order Code 5.50 → Packaging 13.30 Packaging format: Tape & Reel or Loose Reel quantity: \$1621: 5,000 on a Ø330mm reel \$1731: 2,500 on a Ø330mm reel 2.80-₹<sub>0.50 min</sub> \$1911: 4,000 on a Ø330mm reel Recommended PC Board Pattern 6.86mm LONG, 2.54mm HIGH 6.85mm LONG, 0.97mm HIGH - 0.64 1.90 min 0.50 √ min 2.00 2.51 Recommended PC Board Pattern Recommended PC Board Pattern **HOW TO ORDER** S1 XX 1 - 46 R **PACKAGING**

All dimensions in mm.



(P6)

Tape & Reeled

Tin

Blank Loose

**FINISH** 

**SERIES CODE** 

12.3mm long

6.86mm long, 2.54mm high

6.85mm long, 0.97mm high

TYPE 62

**73**