

Smartvest Wireless Magnetic Contact

Art. no. FUMK35000A

Page 1 of 2



- Smartvest extension for monitoring doors and windows
- Quick and cable-free installation without the need for wires or drilling thanks to battery operation
- Tamper protection via cover contact
- Visual notification via blue LED when starting up and functioning
- Automatic supervision, with functional tests repeated daily and feedback sent to the Smartvest alarm control panel
- Low battery notification sent to the Smartvest alarm control panel
- Battery life of up to 1 year
- Small, discreet and secure

The Smartvest Wireless Opening Detector enables you to monitor windows and doors, while its battery operation makes it easy to install, avoiding the need for drilling or wiring. When the battery is low, the Smartvest Wireless Opening Detector sends an automatic notification to the alarm panel about this. The free Smartvest app then guides you step by step through the process of replacing the batteries. In combination with the Smartvest Wireless Socket, you can then initiate certain smart functions such as "open door" or "light on", in addition to monitoring. Compact in size, the Smartvest Wireless Opening Detector is absolutely inconspicuous and blends discreetly into the interior of the room.

Smartvest Wireless Magnetic Contact

Art. no. FUMK35000A

Page 2 of 2

Technical Data:

Areas of usage	Inside
Color	White
Compatible with Secvest	No
Compatible with Smartvest	Yes
Power consumption Standby	0,005 mA
Min. humidity	10
Dimensions (B x L x H)	40 x 14 x 71 mm
Display	LED
Battery operation	Yes
Battery type	CR2032 (3V)
Gross weight	0,092 kg
Wireless modulation	FSK
Radio frequency	868 MHz

Wireless range	(Depending on installation) 30 - 100 m
Housing material	Plastic
Battery quantity	1
Max. battery life	1 y
Max. operating temperature	40 °C
Max. humidity	80 %
Min. operating temperature	0 °C
Net weight	0,03 kg
Tamper protection	Yes
Transmission power	4,5 dBm
Power consumption	15 mA