# **Between-Series Adapters**

## N to TNC


#### N Male Plug to TNC Male Plug

#### Model Number

#### ADT-2584-NM-TNM-02

**SPECIFICATIONS** 

Frequency: DC - 18.0 GHz VSWR: 1.04 @ DC-4.0 GHz 1.07 @ 4.0-8.0 GHz 1.12 @ 8.0-18.0 GHz Impedance: 50 Ohms Finish: Passivated Stainless Steel






#### N Male Plug to TNC Female Jack

#### Model Number ADT-2585-NM-TNF-02 SPECIFICATIONS Frequency: DC - 18.0 GHz VSWR: 1.04 @ DC-4.0 GHz

1.07 @ 4.0-8.0 GHz 1.12 @ 8.0-18.0 GHz Impedance: 50 Ohms Finish: Passivated Stainless Steel





### N Female to TNC Male Plug

## Model Number

ADT-2586-NF-TNM-02


SPECIFICATIONS Frequency: DC - 18.0 GHz VSWR: 1.04 @ DC-4.0 GHz 1.07 @ 4.0-8.0 GHz 1.12 @ 8.0-18.0 GHz Impedance: 50 Ohms Finish: Passivated Stainless Steel

**Model Number** 

ADT-2587-NF-TNF-02


**SPECIFICATIONS** 

Frequency: DC - 18.0 GHz





#### N Female to TNC Female Jack





VSWR: 1.04 @ DC-4.0 GHz 1.07 @ 4.0-8.0 GHz 1.12 @ 8.0-18.0 GHz Impedance: 50 Ohms Finish: Passivated Stainless Steel



# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Cinch Connectivity Solutions: ADT-2587-NF-TNF-02