Angled HDMI Plug to HDMI Receptacle Adaptor

multicomp PRO



Specifications

RoHS Compliant

Adaptor Type : 90° Right Angle / 270° Angle

Convert From : HDMI Plug, 19 Pin
Convert To : HDMI Receptacle, 19 Pin

Colour : Black

Electronic Tests


Open / Short / Intermittence : 100%


 $\begin{array}{ll} \mbox{Hi-Pot} & : AC \ 300\mbox{V}, \ 0.01\mbox{S}, \ 1\mbox{mA} \\ \mbox{Insulation Resistance} & : DC \ 300\mbox{V}, \ 0.01\mbox{S}, \ 10\mbox{M}\mbox{Ω} \mbox{Min}. \end{array}$


Conductive Resistance : 3Ω Max. Computer Test : 1080P @ 60Hz

Diagram

PS000247









PS000269







PIN OUT				
CN1	CN2 CN1	CN2		
1	1 11	11		
2	2 12	12		
3	3 13	13		
4	4 14	14		
5	5 15	15		
6 —	6 16	16		
7	7 17	17		
8	8 18	18		
9	9 19	19		
10	10 Shell	Shel		

Dimensions: Millimetres

No.	Parameter	Specifications
1	Connector - A	HDMI Male, 19 Pin, Gold Plated Shell & Contact
2	Connector - B	HDMI Female, 19 Pin, Gold Plated Shell & Contact
3	PCB	PCB
4	Inner Mold	PE, Transparent
5	Outer Mold	45P, PVC

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Angled HDMI Plug to HDMI Receptacle Adaptor



Part Number Table

Description	Part Number
90° Right Angle HDMI Plug to HDMI Receptacle Adaptor, Black	PS000247
270° Angle HDMI Plug to HDMI Receptacle Adaptor, Black	PS000269

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

