
## **AFM Series**



## Air Flow Monitor





The air-flow monitor provides a simple alternative to indicate positive or negative air flow of fans or blowers. When properly installed and connected in series with an optical (i.e. LED) or audible signaling device, a bi-directional switch will activate an electrical contact if the air flow of the fan falls below 8.2 ft/s, turning the signaling device on or off. The AFM monitor can also be attached to an existing plastic grill or quard.

## **Specifications**

**Contact Type:** Reed/magnet contact

NC (Normally Closed): Contact open with air flow NO (Normally Open): Contact closed with air flow Switching Threshold of Air Flow Speed: >8.2 ft/s

(2.5 m/s)

Hysteresis: 3.3 ft/s (1m/s) - fixed

Contact Resistance Incl. Wire: 370m (1214")

**Service Life:** >100,000 cycles

**Maximum Switching Capacity:** 10W (resistive load) **Maximum Switching Voltage:** NC - AC/DC 240V

NO - DC 60V

Maximum Switching Current: NC - DC 500mA

NO - DC 170mA

**Connection:** 2 x single strand AWG26, length 500mm (20"), tip of stranded wire stripped/tinned 5mm (0/20") NC version (black wires), NO version (blue wires)

**Mounting:** Attachment clamp and/or clip, or integrated in

protective plastic grill

Mounting Position: Air-flow monitoring opening

perpendicular to air flow

**Operating Temperature:** -20 to 50°C (-4 to 122°F) **Storage Temperature:** -20 to 80°C (-4 to 176°F)

**Housing:** Plastic, UL 94HB, black

**Dimensions:** 34 x 17.5 x 7.5mm (1.3 x 0.7 x 0.3")

**Protection Type:** NEMA 1 (IP 20)

**Agency Approvals: CE** 

**RoHS** Compliant

Model No.	Description	Weight
AFM-01NC	Air-flow switch, NC with mounting clip and clamp (for attaching to existing fan assembly)	6 g (0.2 oz)
AFM-01NO	Air-flow monitor, NO with mounting clip and clamp (for attaching to existing fan assembly)	6 g (0.2 oz)
AFM-80NC	Air-flow monitor, NC with 80 x 80mm (3.15") plastic finger guard	20 g (0.7 oz)
AFM-80NO	Air-flow monitor, NO with 80 x 80mm (3.15") plastic finger guard	20 g (0.7 oz)
AFM-92NC	Air-flow monitor, NC with 92 x 92mm (3.62") plastic finger guard	20 g (0.7 oz)
AFM-92NO	Air-flow monitor, NO with 92 x 92mm (3.62") plastic finger guard	20 g (0.7 oz)
AFM-120NC	Air-flow monitor, NC with 120 x 120mm (4.27") plastic finger guard	31 g (1.1 oz)
AFM-120NO	Air-flow monitor, NO with 120 x 120mm (4.27") plastic finger guard	31 g (1.1 oz)

#### **AFM-KIT**

Kit includes air-flow switch (AFM-01NC), clip, three plastic guards (80, 92 and 120mm), LED and holder, buzzer, switch and wall-mount power supply. Delivered with a complete 10-foot wire assembly.



# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Orion Fans:

AFM-92NC AFM-80NC AFM-92NO AFM-120NC AFM-01NC AFM-120NO AFM-01NO AFM-80NO AFM-KIT