



Quad Output DC Power Supply

4-in-1 Power Supply

Four power supplies built into one — Two fully adjustable supplies combined with two auxiliary outputs

Features:

- Two 0 to 30V/0 to 5A outputs with selectable Constant Voltage and Constant Current modes
- Outputs up to 60V in series mode or 10A in parallel mode
- Two auxiliary outputs with fixed current of 3 to 6.5V/3A and 8 to 15V/1A
- · Overload and short circuit protection
- Complete with power cord and 4 pairs of test leads (banana plug to alligator clip)





Single power supply with multiple DC outputs

| Specifications | Range |
|-------------------------|--|
| Output Voltage (4) | 0 to 30V, 0 to 30V, 3 to 6.5V,8 to 15V |
| Output Current (4) | 0 to 5A, 0 to 5A, 3A (fixed), 1A (fixed) |
| Load Voltage Regulation | 0.5mV ±3mV |
| Line Voltage Regulation | 0.1mV ±3mV |
| Load Current Regulation | 2mA ±5mA |
| Line Current Regulation | 2mA ±3mA |
| Ripple and Noise | <0.5mVrms |
| Power | 110 to 240VAC, 50/60Hz (Switchable) |
| Dimensions | 10.2 x 6.3 x 14.5" (260 x 160 x 370mm) |
| Weight | 26.5lbs (12kg) |

Ordering Information:

382270Quad Output DC Power Supply

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Extech: 382270