




Model number


VBP-HH1-V3.0

AS-Interface Handheld

Features

- Addressing and programming AS-Interface slaves
- Displaying the assigned slave addresses and the status of the inputs
- Setting outputs at the AS-Interface ٠ slave
- Also supports profiles S-7.7.A.7 ٠ (Spec 3.0), S-0.B and S-7.B (AS Interface Safety at Work)
- The slave connection is short-circuit ٠ and overload proof
- Battery charger included with delivery





Electrical connection


Dimensions



AS-Interface + 1

- 2 Digital input for optical addressing adapters
- 3 AS-Interface -
- Digital output for optical addressing adapters 4
- 5 Voltage supply for optical addressing adapters

Indicating / Operating means



AS-Interface specification Operating mode

Indicators/operating means

Display

Keyboard

LC display

Plug-in charging unit, 230 V AC, included in the delivery package

membrane keys, 5 keys

Release date: 2013-06-05 15:03 Date of issue: 2014-01-13 221095_eng.xml

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com



1

AS-Interface Handheld

Electrical specifications	
Operating duration	8 h or \geq 250 read/write procedures for fully charged battery
Power supply	battery mode, please use only battery charger included with delivery to charge (charging time about 14 h) $$
Interface	
Interface type	AS-Interface, short-circuit proof and overload-proof, or optical
Open loop voltage	28 V
Load current	100 mA at 25 V
Ambient conditions	
Ambient temperature	0 40 °C (32 104 °F)
Storage temperature	-20 40 °C (-4 104 °F)
Mechanical specifications	
Protection degree	IP20
Material	
Housing	plastic
Mass	approx. 610 g
Compliance with standards and directi	-
ves	
Directive conformity	
Low Voltage Directive 2006/95/EC	Plug-in charging unit EN 60950-1:2006+A14:2009
EMC Directive 2004/108/EC	Handheld: EN 61326-1:2006 Plug-in charging unit EN 61000-3-2:2006 , EN 61000-3- 3:1995+A1:2001+A2:2005 , EN 55022:1998+A1:2000+A2:2006 , EN 55024:1998+A1:2001+A2:2003
Standard conformity	
Noise immunity	Handheld: EN 61326-1:2006 Plug-in charging unit EN 61000-3-2:2006 , EN 61000-3- 3:1995+A1:2001+A2:2005
Emitted interference	Handheld: EN 61326-1:2006 Plug-in charging unit EN 55022:1998+A1:2000+A2:2006 , EN 55024:1998+A1:2001+A2:2003
Protection degree	EN 60529:2000
Electrical safety	Plug-in charging unit EN 60950-1:2006+A14:2009

Function

The AS-Interface Handheld VBP-HH1-V3.0 is an addressing device according to the AS-Interface specification 3.0.

This addressing device can be used to program AS-Interface slaves and to test part of their functions.

In addition, new functions have been incorporated:

- Permanent data exchange with AS-Inter-• face slaves
- Support of the data exchange with 4E4A slaves in ext. addressing mode
- Indication of the safety code for AS-Interface Safety-at-Work slaves

The AS-Interface connection adapter on the top of the addressing device is used for connecting AS-Interface slaves (sensors, actuators and modules) to the addressing device. The following devices and designs can be connected to the addressing device by directly plugging it onto the AS-Interface connection adapter:

Devices with M12 connector, VariKont M-system, VariKont system, FP design, AS-Interface modules of the types G1 and G4.

For device designs with integrated addressing socket, please use the optional adapter cable.

Accessories

VAZ-PK-1,5M-V1-G

Adapter cable module/hand-held programming device

V1S-TEE-V1/V1S

T-Distributor, M12 connector to M12 socket/connector

V1-W-2M-PVC

Female cordset, M12, 4-pin, PVC cable

VAZ-PK-FK-0,2M-V1-W

Adapter cable G10 module/hand-held programming device

VAZ-9VDC-CHRG-115VAC Power Supply

VAZ-9VDC-CHRG-230VAC Power Supply

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group

2

www.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.co

