

## SA-160BT - Amplifier



**Mini stereo amplifier, 2 x 30 W, with Bluetooth interface, NFC and remote control.**

- Integrated hi-fi audio amplifier
- For speakers with an impedance of 8 Ohm
- Volume control with integrated source selector function, LED indicator
- Near Field Communication (NFC)
- Gold-plated speaker terminals
- 1 stereo input via RCA jacks L/R
- 1 line output via 3.5 mm stereo jack
- Fixed antenna
- Metal housing
- Power supply via supplied PSU

## Technical Data

Channels	:
Zones	:
Power rating	:
Power rating at 2 Ohm	:
Power rating at 4 Ohm	: -
Power rating at 8 Ohm	: 2 x 30 W
Power rating at 100 V	:
Power rating with 4 Ohm bridged operation	:
Power rating with 8 Ohm bridged operation	:
Peak music power output ( $P_{MAX}$ )	: 2 x 60 W
Inputs	: 660 mV/10 k Ohm
Frequency range	: 20-20,000 Hz
Crossover network	:
Crossover frequency	:
Integrated limiter	:
Equalizer bass	: -
Equalizer midrange	:
Equalizer treble	:
S/N ratio	: > 99 dBA
Crosstalk attenuation	:
THD	:
Power supply	: via suppl. PSU
Mains voltage	:
Mains frequency	:
Power consumption, operation	:
Power consumption, standby	:
Standby current	: 100 mA
Alternative operating voltage	:
Alternative power supply	:
Admiss. ambient temp.	: 0-40 °C
Dimensions	: 150x49x122 mm
Width	:
Height	:
Depth	:
Rack spaces, RS	:



---

Weight : 610 g  
Connections : RCA L/R (line),  
spring-load. speaker term.