


**RoHS  
Compliant**



## Description:

### Amplifier and Switches


The 2N3251A is a silicon Planer Epitaxial PNP transistor in JEDEC TO-18 metal case. They are suited for switching and amplifier applications

### Pin Configuration:

1. Emitter
2. Base
3. Collector

## Maximum Ratings:

Characteristic	Symbol	Rating	Unit
Collector-Base Voltage	$V_{CBO}$	60	V
Collector-Emitter Voltage	$V_{CEO}$	60	
Emitter-Base Voltage	$V_{EBO}$	5	
Continuous Collector Current	$I_C$	0.2	A
Total Device Dissipation ( $T_A = +25^\circ\text{C}$ ), Derate above $25^\circ\text{C}$	$P_D$	0.36	mW
Total Device Dissipation ( $T_C = +25^\circ\text{C}$ ), Derate above $25^\circ\text{C}$		2.06	$\text{mW}/^\circ\text{C}$
Operating Junction Temperature Range	$T_J$	-55 to +150	$^\circ\text{C}$
Storage Temperature Range	$T_{stg}$		
Thermal Resistance, Junction-to-Case	$R_{thJC}$	146	$^\circ\text{C}/\text{W}$
Thermal Resistance, Junction-to Ambient	$R_{thJA}$	486	



Dimensions	Min.	Max.
A	5.24	5.84
B	4.52	4.97
C	4.31	5.33
D	0.4	0.53
E	-	0.76
F	-	1.27
G	-	2.97
H	0.91	1.17
J	0.71	1.21
K	12.7	-
I	45°	45°

Dimensions : Millimetres

**Pin Configuration:**

- 1. Emitter
- 2. Base
- 3. Collector

**Part Number Table**

Description	Part Number
Transistor, PNP, 0.2A, 60V, TO-18	2N3251A

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.