

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM21AG102SZ1# from the official website of Murata Manufacturing

BLM21AG102SZ1#

"#" indicates a package specification code.










< List of part numbers with package codes > BLM21AG102SZ1D BLM21AG102SZ1J BLM21AG102SZ1B





Packaging Information





5			

Packaging	Specifications	Minimum Order Quantity	
D	180mm Paper Tape	4000	
J	330mm Paper Tape	10000	
В	Bulk(Bag)	1000	



Automotive Usage

Infotainment

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





BLM21AG102SZ1#

Co., Ltd.

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM21AG102SZ1# from the official website of Murata Manufacturing

"#" indicates a package specification code.



The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM_Aseries generates an impedance from the relatively low frequencies. Therefore BLM_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz).

2 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



BLM21AG102SZ1#

"#" indicates a package specification code.



Shape	SMD	
Size Code (in mm)	2012	
Size Code (in inch)	0805	
Length	2.0mm	
Length Tolerance	±0.2mm	
Width	1.25mm	
Width Tolerance	±0.2mm	
Thickness	0.85mm	
Thickness Tolerance	±0.2mm	
Impedance (at 100MHz)	1000Ω	
Impedance (at 100MHz) Tolerance	±25%	
Rated Current (at 85°C)	600mA	
Rated Current (at 125°C)	600mA	
DC Resistance(max.)	0.27Ω	
Operating Temperature Range	-55°C to 125°C	
Mass(typ.)	0.01g	
Number of Circuit	1	

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date. Please download the latest datasheet of BLM21AG102SZ1# from the official website of Murata Manufacturing Co., Ltd.

BLM21AG102SZ1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

