## Data sheet VARIO<sup>®</sup> SOLO Plug



## **Comfort Overvoltage Protection Plug**

Item No.: 0460x0500

- Protects comfortable against overvoltage from the mains
- Dual function reliability due to operating display and acoustic alarms.
- After a protective circuit for overvoltage protection (thermal fuse, micro fuse), an acoustic signal sounds. The connected device continues to operate.
- With integrated fuse drawer for holding a fuse and spare fuse.
- After the overvoltage protection is triggered, the protection devices can be restored. The defective fuse can be easily removed and replaced with the included replacement fuse.

## **Technical Data**

Voltage  $U_n$ : Rated current (-Power): Max. continuous operation voltage  $U_c$ :  $U_{oc}$ : Protection level Up: Imax (8/20): Fuse: SPD according to EN 61643-11 Socket: Dimensions: 230 V~ 16 A (3600 W) 255 V~ / 50Hz 5000 V L-N < 1,0kV - L/N-PE < 1,5kV 6,5 kA T6,3AH/250 V Type 3 earth contact Type F 73 x 65 x 49 (with plug 85) mm

EAN: Packaging unit: 401209600058 7 5 pieces





Bodo Ehmann GmbH Bensbruchstraße 6 63533 Mainhausen Phone: +49 (0) 6182 9293-0 E-Mail: kontakt@ehmann-gmbh.de Web: www.ehmann-gmbh.de Subject to technical changes. Special designs on request. Date: 10/2014