


Distribution unit





RST compact distribution unit

| Name | Color | Part No. |
|---------------------------------|-------|---------------|
| Distribution unit 5 pole | gray | on request |
| | black | 96.050.0153.1 |

| | |
|------------------------|----------------------------|
| Dimensions (W x L x H) | 104 x 162 x 57.2 mm |
| Input | 1 |
| Outputs | 3 |
| Routing | 3 outputs 230/400V, 20A |
| Prewired with | RST20i5 coding color black |
| Prewired with | 2.5 mm ² |
| Fastening options | yes |

Circuit diagram





RST multi-distribution unit





| Name | Color | Part No. |
|------------------------------------|-------|------------|
| RST multi-distribution unit | black | on request |

Detailed information about the distribution units available in section "Distribution units".

| | |
|-------------------------|----------------------------------|
| Dimensions (W x L x H) | 104 x 162 x 96 mm |
| Fitted as required with | M25 device connectors 2 – 5-pole |
| Input | 1 |
| Outputs | 7 (max.) |
| Prewired with | 2.5 mm ² |
| Fuses | 6.3 or 10A can be integrated |





Accessories

Female connector 4 to 5 pole

| Color | Part No. | Part No. |
|-------|--|--|
| | not captive against loss | captive against loss |
| | Pole 4 to 5 pole | Pole 4 to 5 pole |
| | Safe locking device unused male connectors | Safe locking device unused male connectors |
| gray | 05.565.9953.0 | 99.531.0000.7 |
| black | 05.565.9953.1 | 99.532.0000.7 |

Male connector 4 to 5 pole

| Color | Part No. | Part No. |
|-------|--|--|
| | not captive against loss | captive against loss |
| | Pole 4 to 5 pole | Pole 4 to 5 pole |
| | Safe locking device unused female connectors | Safe locking device unused female connectors |
| gray | Z5.565.9853.0 | 99.529.0000.7 |
| black | Z5.565.9853.1 | 99.530.0000.7 |