

Products > Cameras > Area Scan Cameras > Basler dart

daA4200-30mci (No-Mount) - Basler dart

The Basler daA4200-30mci (No-Mount) BCON for MIPI camera module with the ON Semiconductor AR1335 CMOS sensor delivers 30 frames per second at 13 MP resolution. This model has no mount.



Number 1 + Buy now or add to request cart



Specifications

General Information

Design-In Sample:	08/2019
Order Number	108010

Sensor

Sensor Vendor	ON Semiconductor
Sensor	AR1335
Shutter	Rolling Shutter
Max. Image Circle	1/3"
Sensor Type	CMOS
Resolution (HxV)	4208 px x 3120 px
Resolution	13 MP
Pixel Size (H x V)	1.1 μm x 1.1 μm
Frame Rate	30 fps
Mono/Color	Color

Camera Data

Interface	BCON for MIPI
Pixel Bit Depth	10 bits
Synchronization	free-runsoftware trigger
Image Processing	In-Camera Processing
Exposure Control	programmable via the camera APIautomaticmanual

Downloaded from **Arrow.com**.

Camera Data Digital Input 2 Digital Output 2 ■ 5V DC (via BCON for MIPI interface) Power Requirements Power Consumption 0.6 W (typical) Housing Housing Type Board Level Housing Size (L x W x H) 27 mm x 27 mm x 5.3 mm Lens Mount none Weight (typical) 5g Conformity ■ RoHS Conformity ■ CE ■ FCC GenlCam MIPI CSI-2 UL KC



share

Regular updates on events and product innovations:



Basler on the social networks

Keep in touch with us via the social networks:



i

mail mail









© 2019 Basler AG Glossary Sitemap Legal Info Privacy Statement Legal Notice Terms and Conditions Contact Driving Directions

in share

沪ICP备17041046号-1