Note: This datasheet may be out of date.
Please download the latest datasheet of BLM31KN601BH1# from the official website of Murata Manufacturing

Co., Ltd.

https://www.murata.com/en-eu/products/productdetail?partno=BLM31KN601BH1%23

BLM31KN601BH1#

"#" indicates a package specification code.










< List of part numbers with package codes >

BLM31KN601BH1B BLM31KN601BH1K BLM31KN601BH1L



Appearance & Shape







- 1.The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2.The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLM31KN series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 4ADC.
- 4.150°C guaranteed.



Automotive Usage Powertrain/Safety	
------------------------------------	--



Packaging Information

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	1000
К	330mm Embossed Tape	8000
L	180mm Embossed Tape	2500

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2018/05/21



BLM31KN601BH1#

Note: This datasheet may be out of date

 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM31KN601BH1\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$

Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM31KN601BH1%23

"#" indicates a package specification code.

Number of Circuit

Specifications

Shape	SMD
Size Code (in mm)	3216
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.2mm
Width	1.6mm
Width Tolerance	±0.2mm
Thickness	1.6mm
Thickness Tolerance	±0.2mm
Impedance (at 100MHz)	600Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	2A
Rated Current (at 125°C)	2A
Rated Current (at 150°C)	10mA
DC Resistance(max.)	0.038Ω
Operating Temperature Range	-55°C to 150°C
Mass(typ.)	0.041g

2 of 3

Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/


Last updated : 2018/05/21

^{1.} This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

BLM31KN601BH1#


"#" indicates a package specification code.






In operating temperature exceeding +125°C, derating of current is necessary for BLM31KN_BH1 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics



Derating of Rated Current

Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

